


# **MULTILAYER CERAMIC LOW PASS FILTER**

Page 1 of 3

# RCF-829.000-262000-1608-W-TR

Paramete	Value	Unit	
Frequency Range		698.000 ~ 960.000	MHz
Insertion Loss, max	@ +25 °C	0.6	dB
	@ -40 ~ +85 °C	0.8	dB
Attenuation, min	@ 1554 ~ 1610 MHz	30	dB
	@ 1805 ~ 1830 MHz	30	dB
	@ 2110 ~ 2170 MHz	30	dB
	@ 1710 ~ 2700 MHz	30	dB
VSWR, max	2.0	-	
Impedance	50	Ω	
Moisture Sensitivity Levels	Level 1	-	
Operating Temperature Range		-40 ~ +85	°C
Storage Temperature Range		-40 ~ +85	°C
Storage Condition Before Soldering	Storage Temperature Range	+5 ~ +40	°C
(Included Packaging Material)	Relative Humidity	30 ~ 70	%

#### **Dimension**



Top view	Bottom view	Side view
1 OP VIEW	DOLLOTTI VIEW	Side view

	L	W	Т	Α	В	С	D	E
Dimension (mm)	$1.60 \pm 0.15$	$0.80\pm0.15$	$0.60\pm0.10$	$0.175\pm0.15$	$0.25 \pm 0.15$	$0.25\pm0.15$	$0.50\pm0.15$	$0.20 \pm 0.15$




# **MULTILAYER CERAMIC LOW PASS FILTER**

2000 2 of 3


# RCF-829.000-262000-1608-W-TR

#### CONSTRUCTION

Top view



PIN	Connection	PIN	Connection
1	GND	4	GND
2	I/O	5	I/O
3	GND	6	GND






#### **MULTILAYER CERAMIC LOW PASS FILTER**

1000 2 of 2

# RCF-829.000-262000-1608-W-TR

# **Frequency Characteristics**



Raltron Electronics / RAMI Technology USA, LLC, including its affiliates, employees, agents and other persons acting on its behalf (collectively Raltron/RAMI Tech), disclaim any and all liability for any errors or inaccuracies contained in this data sheet. While Raltron/RAMI Tech has made every reasonable effort ensure the accuracy of all product information, specifications and data contained herein, Raltron/RAMI Tech does not guarantiee that the information is accurate, reliable or current. The product information is provided only for reference purposes only and is subject to on or revision, at any time without notice. Raltron/RAMI Tech does not assume any liability airising out or use of any product described herein and disclaims any warranties expressed or implied. The user of products in such applications shall assume all risks of such use and will agree to hold Raltron/RAMI Tech, harmless against all damages.

Copyright © 2016, Ralltron Electronics / RAMI Technology USA, LLC. All rights reserved. No part of this document may be reproduced in any form without the prior written permission of Raltron Electronics / RAMI Technology USA, LLC.

August 01, 2019